

Table 7.14: PODEM ATPG decision steps for example in Figure 7.22.

| Step | Action |
|------|--|
| 1. | Select path $s - Y$ |
| 2. | Initial objective: Set r to 1 |
| 3. | Backtrace from r |
| 4. | Implications in stack: $A = 0$ |
| 5. | Forward implications: $d = 0, X = 1$ |
| 6. | Initial objective: Set r to 1 |
| 7. | Backtrace from r again |
| 8. | Implications in stack: $A = 0, B = 1$ |
| 9. | Forward implications: $k = 1, m = 0, r = 1, q = 1, Y = 1, s = \overline{D}, u = \overline{D}, v = \overline{D}, Z = 1$. |
| 10. | X-PATH-CHECK shows paths $s - Y$ and $s - u - v - Z$ are blocked (the D-frontier disappeared), so backtrack. |
| 11. | Set $B = 0$ (alternate assignment) |
| 12. | Forward implications: $d = 0, X = 1, m = 1, r = 0$. Conflict – fault not sensitized. Backtrack. |
| 13. | Set $A = 1$ (alternate assignment) |
| 14. | Backtrace from r again. |
| 15. | Set $B = 0$. |
| 16. | Forward implications: $d = 0, X = 1, m = 1, r = 0$. Conflict – fault not sensitized. Backtrack. |
| 17. | Set $B = 1$ (alternate assignment) |
| 18. | Forward implications: $d = 1, m = 1, r = 1, q = 0, s = \overline{D}, v = \overline{D}, X = 0, Y = \overline{D}$, and the fault is tested. |

In the example, since path $s - Y$ has level distance 1 from a PO, and path $s - u - v - Z$ has level distance 2 from a PO, PODEM chooses path $s - Y$ as the fault propagation path. X-PATH-CHECK determines that there is an X path along path $s - Y$ to PO Y , so the *initial objective* is to set r (the driver of s) to a 1 to sensitize the fault. Since both inputs of XOR gate r must be controlled to define r , PODEM picks the hardest-to-control input n with an objective of setting it to 0. This leads to various intermediate objectives listed in Table 7.15, and results in the implication $A = 0$. A forward implication from that results in $d = 0$, and $X = 1$. However, this still does not define r , so backtracing from r occurs again. This leads to the primary input assignment $B = 1$. Forward implications from that are $k = 1, m = 0, r = 1, q = 1, Y = 1, s = \overline{D}, u = \overline{D}, v = \overline{D}$, and $Z = 1$.

At this point, X-PATH-CHECK indicates that the original propagation path, $s - Y$, no longer has an X path to PO Y , and that path $s - u - v - Z$ also cannot propagate a fault effect. The *D-frontier* is $\{ \}$. The algorithm backtracks and chooses the alternate assignment for B , $B = 0$. Forward implications from this yield $d = 0, X = 1, m = 1, r = 0$. There is a conflict at s because the fault is not sensitized, so